

Mode 1 Channel	Mode 2 Channel	Value	Function	Type of control
		224-231	Macro 28	step
		232-239	Macro 29	step
		240-243	Macro 30	step
		244-249	Random macro selection by audio control (Set microphone sensitivity in menu "PErS")	step
		250-255	Auto random macro selection from fast to slow	proportional
7	7	0-31	Shutter,stroke Shutter closed	step
		32-63	No function (shutter open)	step
		64-95	Strobe-effect from slow to fast	proportional
		96-127	No function (shutter open)	step
		128-143	Opening pulse in sequences from slow to fast	proportional
		144-159	Closing pulse in sequences from fast to slow	proportional
		160-191	No function (shutter open)	step
		192-223	Random strobe-effect from slow to fast	proportional
		224-255	No function (shutter open)	step
8	8	0-255	Dimmer intensity Coarse intensity from 0 to 100%	proportional
9		0-255	Dimmer fine Fine intensity	proportional