

channel		function	type of control	effect	decimal		percentage	
16 bit	8 bit							
1	1	X axis, base movement (pan) coarse	proportional	proportional coarse control of the base motor movement	0	255	0%	100%
2	2	X axis, base movement (pan) fine	proportional	proportional fine control of the base motor movement	0	255	0%	100%
3	3	Y axis, yoke movement (tilt) coarse	proportional	proportional coarse control of the yoke motor movement	0	255	0%	100%
4	4	Y axis, yoke movement (tilt) fine	proportional	proportional fine control of the yoke motor movement	0	255	0%	100%
5	5	movement speed	step	standard (fast)	0	10	0%	4%
			step	ultra fast movement (best for programming positions)	11	25	4%	10%
			proportional	vector mode (from fast to slow)	26	127	10%	50%
			proportional	tracking mode (from fast to slow)	128	247	50%	97%
			step	tracking mode (slow)	248	255	97%	100%
6	6	dimmer	proportional	gradual adjustment of luminous intensity from 0 to 100%	0	255	0%	100%
7	7	shutter, strobe and zap effect	step	shutter closed (zap off)	0	9	0%	4%
			proportional	strobe effect with variable speed from slow to fast	10	66	4%	26%
			step	shutter open (zap off)	67	68	26%	27%
			proportional	sequenced pulse effect, slow closing, fast opening (with variable speed from slow to fast)	69	125	27%	49%
			step	shutter open (zap off)	126	127	49%	50%
			proportional	sequenced pulse effect, fast closing, slow opening (with variable speed from fast to slow)	128	184	50%	72%
			step	shutter open (zap off)	185	187	73%	73%
			proportional	random strobe effect, non-synchronised, variable speed from slow to fast	188	244	74%	96%
8	8	iris diaphragm (LIN-Linear)	step	open	0	9	0%	4%
			proportional	from maximum to minimum aperture	10	255	4%	100%
8	8	iris diaphragm (with internal PULS effect)	step	open	0	9	0%	4%
			proportional	from maximum to minimum aperture	10	124	4%	49%
			step	minimum diameter	125	129	49%	51%
			proportional	pulsing with proportional increase in speed	130	189	51%	74%
			step	open	190	192	75%	75%
			proportional	pulse and flash effect with proportional increase in speed	193	255	76%	100%
<b>NOTE 1:</b> the iris diaphragm operation will vary according to the selection made for IRIS on the display panel (linear LIN or with internal PULS effect)								
9	9	focus	proportional	proportional control of focus	0	255	0%	100%
10	10	zoom	proportional	proportional control of zoom from wide beam to narrow	0	255	0%	100%
11	11	rotating gobo selection on wheel 1 (closest to lamp) (STRD standard)	step	no gobo	0	10	0%	4%
				gobo 1	11	40	4%	16%
				gobo 2	41	70	16%	27%
				gobo 3	71	100	28%	39%
				gobo 4	101	130	40%	51%
				gobo 5	131	160	51%	63%
			gobo 6	161	192	63%	75%	
proportional	continuous rotation of the gobo wheel from slow to fast	193	255	76%	100%			
11	11	rotating gobo selection on wheel 1 (SPEC special)	step	no gobo	0	10	0%	4%
			proportional	proportional positioning of gobo wheel 1 at 360°	11	192	4%	75%
			proportional	continuous rotation of gobo wheel from slow to fast	193	255	76%	100%
<b>NOTE 2:</b> depending on the gobo selection on display panel (standard STRD or proportional SPEC) the gobo wheel has a different function								

channel		function	type of control	effect	decimal		percentage	
16 bit	8 bit							
12	12	indexing gobo rotation on wheel 1 through 360°	step	no effect	0	10	0%	4%
			proportional	proportional indexing of the gobos through 360°	11	255	4%	100%
13		fine indexing of the gobos 16 bit	proportional	fine indexing of the gobo (gobo wheel 1)	0	255	0%	100%
14	13	gobo rotation on wheel 1	step	no effect	0	10	0%	4%
			proportional	continuous rotation of the gobo in a clockwise direction with proportional control over decreasing speed	11	131	4%	51%
			step	gobo stop	132	134	52%	53%
			proportional	continuous rotation of the gobo in a counter-clockwise direction with proportional control over increasing speed	135	255	53%	100%
<b>NOTE 3:</b> when channel 12 is set to a level between 0 and 10, gobo rotation (channel 14 at 16bit or channel 13 at 8bit) does not effect indexing, the gobo stops instantly								
15	14	rotating gobo selection on wheel 2 (STRD standard)	step	no gobo	0	10	0%	4%
				gobo 1	11	40	4%	16%
				gobo 2	41	70	16%	27%
				gobo 3	71	100	28%	39%
				gobo 4	101	130	40%	51%
				gobo 5	131	160	51%	63%
				gobo 6	161	192	63%	75%
			proportional	continuous rotation of the gobo wheel from slow to fast	193	255	76%	100%
15	14	rotating gobo selection on wheel 2 (SPEC special)	step	no gobo	0	10	0%	4%
			proportional	proportional positioning of gobo wheel 1 at 360°	11	192	4%	75%
			proportional	continuous rotation of gobo wheel from slow to fast	193	255	76%	100%
<b>NOTE 4:</b> depending on the gobo selection on display panel (standard STRD or proportional SPEC) the gobo wheel has a different function								
16	15	indexing gobo rotation on wheel 2 through 360°	step	no effect	0	10	0%	4%
			proportional	proportional indexing of the gobos through 360°	11	255	4%	100%
17		fine indexing of the gobos 16 bit	proportional	fine indexing of the gobo (gobo wheel 2)	0	255	0%	100%
18	16	gobo rotation on wheel 2	step	no effect	0	10	0%	4%
			proportional	continuous rotation of the gobo in a clockwise direction with proportional control over decreasing speed	11	131	4%	51%
			step	gobo stop	132	134	52%	53%
			proportional	continuous rotation of the gobo in a counter-clockwise direction with proportional control over increasing speed	135	255	53%	100%
<b>NOTE 5:</b> when channel 16 or 15 (16bit or 8bit) is set to a level between 0 and 10, gobo rotation (channel 18 at 16bit or channel 16 at 8bit) does not affect indexing, the gobo stops instantly								
19	17	selecting frost and prisms + rotation	step	no effect	0	10	0%	4%
			proportional	insert frost filter in the optical path	11	99	4%	39%
			step	prism 1	100	105	39%	41%
			proportional	continuous rotation of prism 1 in a counter-clockwise direction, with proportional control over speed from maximum to minimum	106	137	42%	54%
			step	stop rotation prism 1	138	142	54%	56%
			proportional	continuous rotation of prism 1 in a clockwise direction, with proportional control over speed from minimum to maximum	143	174	56%	68%
			step	stop rotation prism 1	175	179	69%	70%
			step	prism 2	180	184	71%	72%
			proportional	continuous rotation of prism 2 in a counter-clockwise direction, with proportional control over speed from maximum to minimum	185	216	73%	85%
			step	stop rotation prism 2	217	221	85%	87%
			proportional	continuous rotation of prism 2 in a clockwise direction, with proportional control over speed from minimum to maximum	222	255	87%	100%

channel		function	type of control	effect	decimal		percentage	
16 bit	8 bit							
20	18	selecting saturated colours from the colour wheel	step	no colour, white beam	0	5	0%	2%
				colour 1	6	14	2%	5%
				colour 2	15	22	6%	9%
				colour 3	23	30	9%	12%
				colour 4	31	38	12%	15%
			proportional	colour 5	39	45	15%	18%
				from colour 5 to colour 1, proportional positioning	46	127	18%	50%
				rainbow effect from fast to slow in an anticlockwise direction	128	190	50%	75%
			rainbow effect from slow to fast in a clockwise direction	191	255	75%	100%	
21	19	cyan	proportional	proportional control of the percentage of cyan colour in the light beam from 0 to 100%	0	255	0%	100%
22	20	magenta	proportional	proportional control of the percentage of magenta colour in the light beam from 0 to 100%	0	255	0%	100%
23	21	yellow	proportional	proportional control of the percentage of yellow colour in the light beam from 0 to 100%	0	255	0%	100%
24	22	conversion filters	step	no colour temperature correction, open beam 7000K	0	58	0%	23%
				control of the colour temperature of the light beam to 6000K	59	106	23%	42%
				control of the colour temperature of the light beam to 5200K	107	154	42%	60%
				control of the colour temperature of the light beam to 4200K	155	202	61%	79%
				control of the colour temperature of the light beam to 3200K	203	250	80%	98%
				control of the colour temperature of the light beam to 10000K	251	255	98%	100%
25	23	zap effect (effect varies depending upon channel 7 strobe)	step	no effect	0	10	0%	4%
				zap effect synchronised with the strobe effect, speed and mode selected by strobe channel 7	11	30	4%	12%
				zap effect, flicker and speed adjustable, speed and mode selected by strobe channel 7	31	249	12%	98%
				black-out of the light beam during PAN/TILT movement, colours and gobos	250	255	98%	100%
26	24	lamp on/off, all motor resets	step	park, no function	0	10	0%	4%
				lamp off	11	29	4%	11%
				pan and tilt reset (once only)	30	65	12%	25%
				reset all motors except black-out, pan and tilt (once only)	66	100	26%	39%
				reset all motors except black-out (once only)	101	135	40%	53%
				reset all motors (once only)	136	170	53%	67%
				lamp on	171	255	67%	100%
<b>Note 6:</b> the display panel may be used to disable the switching off of the lamp via DMX								
<b>Note 7:</b> turning off the lamp and all reset functions are delayed by 6 seconds to prevent accidental activation								
<b>Note 8:</b> the lamp on/off function can only be effected if an opposite level is set								
Projector: coemar iSpot 1200 EB				Table name: DMX 512 functions				
Table number: 230			Edition: 1	Date: 12/11/2004				