

channel	function	type of control	effect	decimal		percentage	
1	X axis, base movement (pan)	proportional	control of the pan movement of the beam of light via proportional rotation of the base motor	0	- 255	0%	- 100%
2	X axis, fine base movement (pan)	proportional	fine control of the pan movement of the beam of light via proportional rotation of the base motor	0	- 255	0%	- 100%
3	Y axis, yoke movement (tilt)	proportional	control of the tilt movement of the beam of light via proportional rotation of the yoke motor	0	- 255	0%	- 100%
4	Y axis, fine yoke movement (tilt)	proportional	fine control of the tilt movement of the beam of light via proportional rotation of the yoke motor	0	- 255	0%	- 100%
5	movement speed	step	standard (fast)	0	- 10	0%	- 4%
		step	ultra fast movement (ideal for positioning during programming)	11	- 25	4%	- 10%
		proportional	vector mode (from fast to slow)	26	- 127	10%	- 50%
		proportional	tracking mode (from fast to slow)	128	- 247	50%	- 97%
		step	tracking mode (slow)	248	- 255	97%	- 100%
6	dimmer	step	closed	0	- 7	0%	- 3%
		proportional	adjust output intensity from 0 to 100%	8	- 255	3%	- 100%
7	shutter, strobe	step	shutter closed	0	- 9	0%	- 4%
		proportional	variable speed strobing effect, from slow to fast	10	- 66	4%	- 26%
		step	shutter open	67	- 68	26%	- 27%
		proportional	sequenced pulse effect, slow closing, fast opening (variable speed pulsing, from slow to fast)	69	- 125	27%	- 49%
		step	shutter open	126	- 127	49%	- 50%
		proportional	sequenced pulse effect, fast closing, slow opening (variable speed pulsing, from fast to slow)	128	- 184	50%	- 72%
		step	shutter open	185	- 187	73%	- 73%
		proportional	random strobe effect with variable speed from slow to fast	188	- 244	74%	- 96%
8	zoom	step	spot	0	- 9	0%	- 4%
		proportional	from narrow beam (Spot) to wide beam (Flood)	10	- 255	4%	- 100%
9	PAR effect filter, CTO filter	step	no effect	0	- 9	0%	- 4%
		proportional	oval beam (par effect) rotatable through 0° to 180°	10	- 230	4%	- 90%
		step	CTO conversion filter	231	- 255	91%	- 100%

channel	function	type of control	effect	decimal	percentage
10	colour wheel	step	no colour, white beam	0 - 7	0% - 3%
		step or proportional control selectable via channel 14	colour 1	8 - 27	3% - 11%
			colour 2	28 - 47	11% - 18%
			colour 3	48 - 67	19% - 26%
			colour 4	68 - 87	27% - 34%
			colour 5	88 - 107	35% - 42%
			colour 6	108 - 127	42% - 50%
		proportional	rainbow effect in a counterclockwise direction from fast to slow	128 - 190	50% - 75%
step	no rotation	191 - 192	75% - 75%		
proportional	rainbow effect in a clockwise direction from slow to fast	193 - 255	76% - 100%		
11	cyan	step	white, no colour	0 - 9	0% - 4%
		proportional	proportional control of the cyan colour, from white to full cyan	10 - 255	4% - 100%
12	magenta	step	white, no colour	0 - 9	0% - 4%
		proportional	proportional control of the magenta colour, from white to full magenta	10 - 255	4% - 100%
13	yellow	step	white, no colour	0 - 9	0% - 4%
		proportional	proportional control of the yellow colour, from white to full yellow	10 - 255	4% - 100%
14	colour positioning mode (colour selection via channel 10)	step	colours are centred in the optical path	0 - 125	0% - 49%
			colour are positioned proportionately in the optical path	126 - 255	49% - 100%
15	activate black-out synchronised with PAN/TILT movement and colour changing	step	no effect	0 - 249	0% - 98%
			black-out of the beam light during PAN/TILT movement and colour changing	250 - 255	98% - 100%
16	lamp on/off, motors reset	step	park, no effect	0 - 10	0% - 4%
			lamp off	11 - 29	4% - 11%
			pan and tilt reset (only once)	30 - 65	12% - 25%
			reset all motors except dimmer, pan and tilt (only once)	66 - 100	26% - 39%
			reset all motors except dimmer (only once)	101 - 135	40% - 53%
			reset all motors (only once)	136 - 170	53% - 67%
			fans at maximum speed (only when lamp on)	171 - 249	67% - 98%
			lamp on, fans off (if internal temperature allows)	250 - 255	98% - 100%
Note 1: the display panel may be used to disable the switching off of the lamp via DMX					
Note 2: turning off the lamp and all the reset functions are delayed by 6 seconds to prevent accidental activation					
Note 3: lamp On/Off function and fan status can be modified only if an opposite level is set					
Projector: coemar i Wash 575 MB			Table name: DMX 512 functions		
Table number: 226		Edition: 0	Date: 18/05/2004		