

Robin Actor 12 - DMX chart

Version 1.2

Mode/Channel						Value	Function	Type of control
1	2	3	4	5	6			
					1		No function	
					2		No function	
					3		No function	
					4		No function	
					5		No function	
1	1	1	1	1	6	0 - 9	Special functions Reserved <i>To activate following functions , stop in DMX value for at least 3sec. and shutter must be closed at least 3sec. (Shutter channel 38/14/9/4/4/43 must be at range of 0-31DMX). Corresponding menu items are temporarily overrided except DMX Input.</i>	
						10 - 14	DMX input: Wired DMX *	step
						15 - 19	DMX input: Wireless DMX* * function is active only 10 seconds after switching the fixture on	step
						20-29	Reserved	
						30-39	RGBW colour mixing mode	step
						40-49	CMY colour mixing mode	step
						50-169	Reserved <i>To activate following reset function, stop in DMX value for at least 3 sec.</i>	
						170 - 179	Save current DMX values into fixture **	step
						180 - 189	Zoom reset	step
						190 - 199	Reserved	
						200 - 209	Total reset	step
						210 - 239	Reserved	
						240	Disable "Silent mode" of fans	step
						241 - 255	"Silent mode of fans":fans noise from min. to max.	proportional
-	2	2	-	-	-	0-255	Red/Cyan (8 bit) - all zones Red or cyan LEDs saturation control (0-100%)	proportional
-	3	-	-	-	-	0-255	Red/Cyan fine(16 bit) - all zones Fine red or cyan LEDs saturation control	proportional
-	4	3	-	-	-	0-255	Green/Magenta (8 bit) - all zones Green or magenta LEDs saturation control(0-100%)	proportional
-	5	-	-	-	-	0-255	Green/Magenta fine (16 bit) - all zones Fine green or magenta LEDs saturation control	proportional
-	6	4	-	-	-	0-255	Blue/Yellow (8 bit) - all zones Blue or yellow LEDs saturation control (0-100%)	proportional
-	7	-	-	-	-	0-255	Blue/Yellow fine (16 bit) - all zones Fine blue or yellow LEDs saturation control	proportional
-	8	5	-	-	-	0-255	White (8 bit) - all zones <i>If RGBW mode is selected:</i> White colour saturation control coarse (0-100%) <i>If CMY mode is selected:</i> No function	proportional
-	9	-	-	-	-	0-255	White fine (16 bit) - all zones Fine white LEDs saturation control (RGBW mode)	proportional
2	-	-	-	9	7	0-255	Red/Cyan (8 bit) - zone 1 Red or cyan LEDs saturation control (0-100%)	proportional
3	-	-	-	10	8	0-255	Red/Cyan fine (16 bit) - zone 1 Fine red or cyan LEDs saturation control	proportional

Mode/Channel						Value	Function	Type of control
1	2	3	4	5	6			
4	-	-	-	11	9	0-255	Green/Magenta (8 bit) - zone 1 Green or magenta LEDs saturation control(0-100%)	proportional
5	-	-	-	12	10	0-255	Green fine (16 bit) - zone 1 Fine green or magenta LEDs saturation control	proportional
6	-	-	-	13	11	0-255	Blue/Yellow (8 bit) zone 1 Blue or yellow LEDs saturation control (0-100%)	proportional
7	-	-	-	14	12	0-255	Blue/Yellow (16 bit) zone 1 Fine blue or yellow LEDs saturation control)	proportional
8	-	-	-	15	13	0-255	White (8 bit) - zone 1 <i>If RGBW mode is selected:</i> White colour saturation control coarse (0-100%) <i>If CMY mode is selected:</i> No function	proportional
9	-	-	-	16	14	0-255	White (16 bit) - zone 1 Fine white LEDs saturation control (RGBW)	proportional
10	-	-	-	17	15	0-255	Red/Cyan (8bit) - zone 2 Red or cyan LEDs saturation control (0-100%)	proportional
11	-	-	-	18	16	0-255	Red/Cyan fine (16 bit) - zone 2 Fine red or cyan LEDs saturation control	proportional
12	-	-	-	19	17	0-255	Green/Magenta (8 bit) - zone 2 Green or magenta LEDs saturation control(0-100%)	proportional
13	-	-	-	20	18	0-255	Green/Magenta fine (16 bit) - zone 2 Fine green or magenta LEDs saturation control	proportional
14	-	-	-	21	19	0-255	Blue/Yellow (8 bit) - zone 2 Blue or yellow LEDs saturation control (0-100%)	proportional
15	-	-	-	22	20	0-255	Blue/Yellow fine (16 bit) - zone 2 Fine blue or yellow LEDs saturation control	proportional
16	-	-	-	23	21	0-255	White (8 bit) - zone 2 <i>If RGBW mode is selected:</i> White colour saturation control coarse (0-100%) <i>If CMY mode is selected:</i> No function)	proportional
17	-	-	-	24	22	0-255	White (16 bit) - zone 2 Fine white LEDs saturation control (RGBW mode)	proportional
18	-	-	-	25	23	0-255	Red/Cyan (8 bit) - zone 3 Red or cyan LEDs saturation control (0-100%)	proportional
19	-	-	-	26	24	0-255	Red/Cyan fine (16 bit) - zone 3 Fine red or cyan LEDs saturation control	proportional
20	-	-	-	27	25	0-255	Green/Magenta (8 bit) - zone 3 Green or magenta LEDs saturation control(0-100%)	proportional
21	-	-	-	28	26	0-255	Green/Magenta fine (16 bit) - zone 3 Fine green or magenta LEDs saturation control	proportional
22	-	-	-	29	27	0-255	Blue/Yellow (8 bit) zone 3 Blue or yellow LEDs saturation control (0-100%)	proportional
23	-	-	-	30	28	0-255	Blue/Yellow fine (16 bit) zone 3 Fine blue or yellow LEDs saturation control	proportional
24	-	-	-	31	29	0-255	White (8 bit) zone 3 <i>If RGBW mode is selected:</i> White colour saturation control coarse (0-100%) <i>If CMY mode is selected:</i> No function	proportional
25	-	-	-	32	30	0-255	White fine (16 bit) zone 3 Fine white LEDs saturation control (RGBW mode)	proportional

Mode/Channel						Value	Function	Type of control
1	2	3	4	5	6			
26				33	31	0-255	Red/Cyan (8 bit) - zone 4 Red or cyan LEDs saturation control (0-100%)	proportional
27				34	32	0-255	Red/Cyan fine (16 bit) - zone 4 Fine red or cyan LEDs saturation control	proportional
28				35	33	0-255	Green/Magenta (8 bit) - zone 4 Green or magenta LEDs saturation control(0-100%)	proportional
28				36	34	0-255	Green/Magenta fine (16 bit) - zone 4 Fine green or magenta LEDs saturation control	proportional
30				37	35	0-255	Blue/Yellow (8 bit) zone 4 Blue or yellow LEDs saturation control (0-100%)	proportional
31				38	36	0-255	Blue/Yellow fine (16 bit) zone 4 Fine blue or yellow LEDs saturation control	proportional
32				39	37	0-255	White (8 bit) zone 4 <i>If RGBW mode is selected:</i> White colour saturation control coarse (0-100%) <i>If CMY mode is selected:</i> No function	proportional
33				40	38	0-255	White fine (16 bit) zone 4 Fine white LEDs saturation control (RGBW mode)	proportional
34	10	6	-	7	39	0 1-255	CTC No function Colour temperature correction from 20000K to 2700K)	step proportional
35	11	7	2	8	40	0 1-2 3 4-5 6 7-9 10-12 13-15 16 17-55 56 57 - 95 96 97 - 134 135 136 - 174 175 176 - 214 215 216 - 246 247 ----- 248 249 250 251 252 253 254 255	Virtual Colour Wheel For detailed description see " Virtual colour wheel- colour mixing chart No function White 2700 K White 2700 K (Halogen lamp mode***) White 3200 K White 3200 K (Halogen lamp mode***) White 4200 K White 5600 K White 8000 K Blue (Blue=full, Red+Green+White=0) Red=0, Green->up,Blue =full, White=0 Light Blue (Red=0, Green=full, Blue =full, White=0) Red=0, Green=full, Blue->down, White=0 Green (Red=0, Green=full, Blue =0, White=0) Red->up, Green=full, Blue=0, White=0 Yellow (Red=full, Green=full, Blue=0, White=0) Red=full, Green->down, Blue=0, White=0 Red(Red=full, Green=0, Blue=0, White=0) Red=full, Green=0, Blue->up, White=0 Magenta (Red=full, Green=0, Blue=full, White=0) Red -> down, Green=0, Blue=full, White=0 Blue (Red=0, Green=0, Blue=full, White=0) ----- <i>Speed of the following effects can be controlled by the Shutter/Strobe channel (DMX values of 96-127)</i> Rainbow effect (with fade time) Rainbow effect Zone effect 1 Zone effect 2 Zone effect 3 Zone effect 4 Zone effect 5 Zone effect 6	step step step step step step step step step step proportional step proportional step proportional step proportional step step step step step step step step step

Mode/Channel						Value	Function	Type of control				
1	2	3	4	5	6							
36	12	8	3	2	41	0 - 255	Zoom (8 bit) Zoom from min. to max. beam angle	proportional				
37	13	-	-	3	42	0 - 255	Zoom fine (16 bit) Fine zooming from min. to max.	proportional				
38	14	9	4	4	43	0-31	Shutter closed	step				
						32-63	Strobe effect from slow--> fast (zone 4 only)	proportional				
						64-95	Strobe effect from slow--> fast (All zones together)	proportional				
						-----Set value on Virtual colour wheel-----						
						96-111	Zone effects+rainbow effects speed control, slow--> fast	proportional				
						112-127	Zone effects+rainbow effects speed control, fast--> slow /opposite direction/	proportional				
						128-143	Opening pulses in sequences from slow--> fast (All zones together)	proportional				
						144-159	Closing pulses in sequences from fast--> slow (All zones together)	proportional				
160-175	Random strobe effect from slow--> fast (random zone)	proportional										
176-191	Random strobe effect from slow--> fast (random zone + random strobe)	proportional										
192-223	Random strobe effect from slow --> fast (All zones together)	proportional										
224-239	Random strobe effect from slow --> fast (random LEDs)	proportional										
240-255	Shutter open	step										
39	15	10	5	5	44	0-255	Dimmer (8 bit) Dimmer intensity from 0% to 100%	proportional				
40	16	-	-	6	45	0-255	Dimmer fine (16 bit) Fine dimming	proportional				

** DMX values of all channels are saved into fixture and will be recall after switching the fixture on (without DMX controller connected).

***In the Halogen lamp mode the Dimmer channel imitates behaviour of the halogen lamp during dimming.

Virtual colour wheel - colour mixing chart

Scale*	Virtual Colour Wheel	Red	Green	Blue	White
	DMX	DMX	DMX	DMX	DMX
1-15	1-2 (White 2700K)	250	118	0	63
	3 (White 2700K /Hal.mode/)	250	118	0	63
	4-5 (White 3200K)	255	141	5	89
	6 (White 3200K /Hal.mode/)	255	141	5	89
	7-9 (White 4200K)	254	141	3	255
	10-12 (White 5600K)	254	207	37	255
	13-15 (White 8000K)	228	255	79	255
16-63	16	0	0	255	0
	17	0	3	255	0
	18	0	6	255	0
	19	0	9	255	0
	20	0	12	255	0
	21	0	15	255	0
	22	0	18	255	0
	23	0	21	255	0
	24	0	24	255	0
	25	0	27	255	0
	26	0	30	255	0
	27	0	36	255	0
	28	0	41	255	0
	29	0	46	255	0
	30	0	52	255	0
	31	0	58	255	0
	32	0	64	255	0
	33	0	68	255	0
	34	0	74	255	0
	35	0	80	255	0
	36	0	86	255	0
	37	0	92	255	0
	38	0	98	255	0
	39	0	104	255	0
	40	0	110	255	0
	41	0	119	255	0
	42	0	129	255	0
	43	0	138	255	0
	44	0	147	255	0
	45	0	156	255	0
	46	0	165	255	0
	47	0	174	255	0
	48	0	183	255	0
	49	0	192	255	0
	50	0	201	255	0
	51	0	210	255	0
	52	0	219	255	0
	53	0	228	255	0
	54	0	237	255	0
	55	0	246	255	0
	56	0	255	255	0
	57	0	255	246	0
	58	0	255	237	0
	59	0	255	228	0
	60	0	255	219	0
	61	0	255	210	0
	62	0	255	201	0
	63	0	255	192	0

Scale*	Virtual Colour Wheel DMX	Red DMX	Green DMX	Blue DMX	White DMX
	64	0	255	183	0
	65	0	255	174	0
	66	0	255	165	0
	67	0	255	156	0
	68	0	255	147	0
	69	0	255	138	0
	70	0	255	129	0
	71	0	255	119	0
	72	0	255	110	0
	73	0	255	104	0
	74	0	255	98	0
	75	0	255	92	0
	76	0	255	86	0
	77	0	255	80	0
	78	0	255	74	0
	79	0	255	68	0
	80	0	255	64	0
	81	0	255	58	0
	82	0	255	52	0
	83	0	255	46	0
	84	0	255	41	0
	82	0	255	36	0
	86	0	255	30	0
	87	0	255	27	0
	88	0	255	24	0
	89	0	255	21	0
	90	0	255	18	0
	91	0	255	15	0
	92	0	255	12	0
	93	0	255	9	0
	94	0	255	6	0
	95	0	255	3	0
	96	0	255	0	0
	97	3	255	0	0
	98	6	255	0	0
	99	9	255	0	0
	100	12	255	0	0
	101	15	255	0	0
	102	18	255	0	0
	103	21	255	0	0
	104	24	255	0	0
	105	27	255	0	0
	106	30	255	0	0
	107	36	255	0	0
	108	41	255	0	0
	109	46	255	0	0
	110	52	255	0	0
	111	58	255	0	0
	112	64	255	0	0
	113	68	255	0	0
	114	74	255	0	0
	115	80	255	0	0
	116	86	255	0	0
	117	92	255	0	0
	118	98	255	0	0

Scale*	Virtual Colour Wheel	Red	Green	Blue	White
	DMX	DMX	DMX	DMX	DMX
	119	104	255	0	0
	120	110	255	0	0
	121	119	255	0	0
	122	129	255	0	0
	123	138	255	0	0
	124	147	255	0	0
	125	156	255	0	0
	126	165	255	0	0
	127	174	255	0	0
	128	183	255	0	0
	129	192	255	0	0
	130	201	255	0	0
	131	210	255	0	0
	132	219	255	0	0
	133	228	255	0	0
	134	240	255	0	0
	135	255	255	0	0
	136	255	246	0	0
	137	255	237	0	0
	138	255	228	0	0
	139	255	219	0	0
	140	255	210	0	0
	141	255	201	0	0
	142	255	192	0	0
	143	255	183	0	0
	144	255	174	0	0
	145	255	165	0	0
	146	255	156	0	0
	147	255	147	0	0
	148	255	138	0	0
	149	255	129	0	0
	150	255	119	0	0
	151	255	110	0	0
	152	255	104	0	0
	153	255	98	0	0
	154	255	92	0	0
	155	255	86	0	0
	156	255	80	0	0
	157	255	74	0	0
	158	255	68	0	0
	159	255	64	0	0
	160	255	58	0	0
	161	255	52	0	0
	162	255	46	0	0
	163	255	41	0	0
	164	255	36	0	0
	165	255	30	0	0
	166	255	27	0	0
	167	255	24	0	0
	168	255	21	0	0
	169	255	18	0	0
	170	255	15	0	0
	171	255	12	0	0
	172	255	9	0	0
	173	255	6	0	0

Scale*	Virtual Colour Wheel	Red	Green	Blue	White
	DMX	DMX	DMX	DMX	DMX
	174	255	3	0	0
	175	255	0	0	0
	176	255	0	3	0
	177	255	0	6	0
	178	255	0	9	0
	179	255	0	12	0
	180	255	0	15	0
	181	255	0	18	0
	182	255	0	21	0
	183	255	0	24	0
	184	255	0	27	0
	185	255	0	30	0
	186	255	0	36	0
	187	255	0	41	0
	188	255	0	46	0
	189	255	0	52	0
	190	255	0	58	0
	191	255	0	64	0
	192	255	0	68	0
	193	255	0	74	0
	194	255	0	80	0
	195	255	0	86	0
	196	255	0	92	0
	197	255	0	98	0
	198	255	0	104	0
	199	255	0	110	0
	200	255	0	119	0
	201	255	0	129	0
	202	255	0	138	0
	203	255	0	147	0
	204	255	0	156	0
	205	255	0	165	0
	206	255	0	174	0
	207	255	0	183	0
	208	255	0	192	0
	209	255	0	201	0
	210	255	0	210	0
	211	255	0	219	0
	212	255	0	228	0
	213	255	0	237	0
	214	255	0	246	0
	215	255	0	255	0
	216	246	0	255	0
	217	237	0	255	0
	218	228	0	255	0
	219	219	0	255	0
	220	210	0	255	0
	221	201	0	255	0
	222	192	0	255	0
	223	183	0	255	0
	224	174	0	255	0
	225	165	0	255	0
	226	156	0	255	0
	227	147	0	255	0
	228	138	0	255	0

Scale*	Virtual Colour Wheel	Red	Green	Blue	White
	DMX	DMX	DMX	DMX	DMX
	229	129	0	255	0
	230	119	0	255	0
	231	110	0	255	0
	232	104	0	255	0
	233	98	0	255	0
	234	91	0	255	0
	235	84	0	255	0
	236	77	0	255	0
	237	70	0	255	0
	238	63	0	255	0
	239	56	0	255	0
	240	49	0	255	0
	241	42	0	255	0
	242	35	0	255	0
	243	28	0	255	0
	244	21	0	255	0
	245	14	0	255	0
	246	7	0	255	0
	247	0	0	255	0
	248-255 (Rainbow+ zone effects)	****	****	****	****
* Colour scale as an illustration only					