

# MaxModule Playback™ Specifications

The Playback module extends the playback capabilities of any M-Series console by adding 10 motorized faders with 15 LCD buttons and a master Go section. Up to 16 Playback modules can be added to any MaxModule Cerebrum, Maxxyz, M-Series consoles or M-PC V3.

## Features

- 10 x motorized playback faders, each with one dynamically labeled LCD button (to identify/activate playback) and two function-assignable buttons

- 10 x pause/back buttons

- 10 x go buttons

- 10 x flash buttons

- 5 x LCD navigation buttons with scroll wheel

- Master Go section

- Built-in Maxxyz PC dongle and 2 built-in DMX ports

## Physical

Length: 275 mm (10.8 in.)

Width: 483 mm (19.0 in.)

Height: 128 mm (5.0 in.)

Weight: 4.6 kg (10.1 lbs.)

## Control/User Interface

- 10 x motorized playback faders, each with one dynamically labeled LCD button (to identify/activate playback) and two function-assignable buttons

- 10 x pause/back buttons

- 10 x go buttons

- 10 x flash buttons

- 5 x LCD navigation buttons with scroll wheel

- Master Go section

## Connections

Maxxyz/Maxedia multiple controller link USB: Neutrik locking RJ45 Ethercon sockets

DMX out: 2 x 5-pin female locking XLR

USB input: USB device socket

USB devices: USB host socket

Desk lamp: 2.5 mm (0.1 in.) DC bayonet

AC power input: 3-pin IEC male socket

AC power throughput: 3-pin IEC female socket

## Electrical

AC power: 100-240 V nominal, 50/60 Hz

Power supply unit: Auto-ranging electronic switch-mode

Main fuse: 2 AT (slow blow)

Desk lamp output: 12 V

AC power output: Unswitched, unfused, max. 6 A

## Approvals



EU safety: EN 60950

EU EMC: EN 55022, EN 55024, EN 61000-3-2, EN 61000-3-3

US safety (pending): ANSI/UL 60950-1

Canadian safety (pending): CSA C22.2 No. 60950-1