

COLORMIX 150 AT WASH - DMX Protocol 8-bit

Channel	Value	Function	Type of control
1	0	Colours Open/white	proportional
	10	Turquoise	proportional
	21	Red	proportional
	32	Cyan	proportional
	42	Light green	proportional
	53	Magenta	proportional
	64	Light Blue	proportional
	74	Yellow	proportional
	85	Green	proportional
	96	Pink	proportional
	106	Blue	proportional
	117	Orange	proportional
	128-189	Forwards rainbow effect from fast to slow	proportional
190-193	No rotation	proportional	
194-255	Backwards rainbow effect from slow to fast	proportional	
2	0-255	Dimmer intensity Intensity from 0 to 100%	proportional
3	0	Shutter,Strobe,Reset Shutter closed	step
	1-63	Light intensity from 0 to 100%	proportional
	64-95	Shutter open	step
	96-127	Strobe-effect from slow to fast (max 8 flashes/s)	proportional
	128-139	Reset	step
	140-159	Shutter closed	step
	160-175	Pulse-effect in sequences with increasing speed	proportional
	176-191	Pulse-effect in sequences with decreasing speed	proportional
	192-223	Random strobe effect with increasing speed	proportional
	224-255	Shutter open	step