

DMX functions

The Roadie Compact's address setting must match the DMX address allocated to it on the controller. To set the address, see "Setting the DMX base address" on page 14. The Roadie Compact requires two DMX channels.

DMX channel	function
1	Fog density 0-100%
2	Fan speed 0-100% and Shutdown

Channel 1 uses the full range 0-255 for fog density control.
Channel 2 has the following control values.

DMX value	function
0-244	Fan speed 0-100%, heaters on
245-255	machine shutdown, heaters off